

I/O Karte für Tastatur und Drucker 3

(SAAG31) AAG31

I/O Board for keyboard and printer 3

701.81764

Position-Nr. Position-No.	Typ Type	Teil-Nr. Part-No.	Bemerkung Remarks
<u>IC - Bausteine / IC - chips</u>			
IC 50,101	SN 7400 N	E 600.37001	A 01
IC 43,46	SN 7402 N	E 600.37003	A 02
IC 1,15,61, 75,87,96, 103	SN 7404 N	E 600.37006	A 03
IC 8	SN 7430 N	E 600.37008	A 06
IC 22,71	SN 7405 N	E 600.37024	A 11
IC 47,54	SN 7407 N	E 600.37025	A 12
IC 29,36,58, 65,94	SN 7437 N	E 600.37027	A 18
IC 7I,7II, 14I,14II, 28I,28II, 35I,35II, 42I,42II, 49I,49II	SN 75453 N	E 600.37058	A 28
IC 6,13, 25-27,32, 34,41,48, 55,57,59, 67,74,88, 95,102	SN 7475 N	E 600.37040	F 04
IC 85,86,100	SN 7474 N	E 600.37042	F 06
IC 68,99,110	SN 74132 N	E 600.37052	G 04
IC 93II	NE 555 N	E 600.38013	G 05
IC 106,107	SN 74221 N	E 600.37048	G 06
IC 2,9,16, 23,30,37, 44,51	SN 74151 N	E 600.37015	H 02
IC 64,92	SN 74155 N	E 600.37050	H 05
IC 12	SN 7493 N	E 600.37021	P 01

Position-Nr. Position-No.	Typ Type	Teil-Nr. Part-No.	Bemerkung Remarks
<u>Transistoren / Transistors</u>			
T 2-5,7, 8,11,14, 16-22, 24-27	BD 675 MPSU 45	E 600.63046 E 600.63041) wahlweise) alternatively
T 6,9,10, 12,13,15, 23	BD 679	E 600.63047	
<u>Dioden / Diodes</u>			
D 2,4-21	1 N 4001	E 600.64042	
D 1	ZPD 8,2	E 600.64108	
<u>Kondensatoren / Capacitors</u>			
C 69,75	220 μ F 40 V	E 600.50010	
C 1,51	100 μ F 16 V 100 μ F 16 V	E 600.50061 E 600.50070) wahlweise) alternatively
C 34,35, 4-18, 21-32,52, 57,60,61, 76,77,79, 39-46	0,1 μ F 100 V	E 600.52032	
C 73	47 μ F 16 V 47 μ F 16 V	E 600.50069 E 600.50060) wahlweise) alternatively
C 62,63,66, 68,70,71	10 μ F 25 V	E 600.50055	
C 56	0,022 μ F 160 V	E 600.52044	
C 53	0,022 μ F 100 V	E 600.52030	
C 58	1000 pF 100 V	E 600.52025	
C 50,54	680 pF 50 V	E 600.53015	

Position-Nr. Position-No.	Typ Type		Teil-Nr. Part-No.	Bemerkung Remarks
<u>Kondensatoren / Capacitors</u>				
C 2,3,20, 47-49, 55,59,64, 65,67,72, 74,78	0,1 μ F	16 V	E 600.53010	
<u>Widerstände / Resistors</u>				
R 53,54,59, 60,62,68, 69-71,87, 89,61,120	47 Ohm	1/8 W	E 600.40205	
R 93,119	470 Ohm	1/8 W	E 600.40193	
R 88,90,96, 121	1 kOhm	1/8 W	E 600.40195	
R 81	15 kOhm	1/8 W	E 600.40224	
R 91	2,2 kOhm	1/8 W	E 600.40212	
R 47,48,50, 51,55-58	4,7 kOhm	1/8 W	E 600.40197	
R 27-30, 1,2,32, 4-25,49, 52,82,92, 94,95,98, 100-108, 36-46	10 kOhm	1/8 W	E 600.40200	
R 63-65, 74-80	100 Ohm	1/4 W	E 600.40108	
R 83,84	1,5 kOhm	1/3 W	E 600.40033	
R 97	120 kOhm	1/4 W	E 600.40145	

Position-Nr. Position-No.	Typ Type	Teil-Nr. Part-No.	Bemerkung Remarks
<u>Widerstände / Resistors</u>			
R 66,67,72, 73,109-118	100 Ohm 2 W	E 600.40181	
R 122	6,8 kOhm 1/8W	E 600.40202	
R 3,85,86	10 kOhm 1/2W	E 600.44033	
<u>Allgemeine Teile / General parts</u>			
Sch 1,2	0,1 A 100 V	E 600.85059 E 600.85073	Schalter) wahlweise Switch) alternatively
M 60,72,78, 79,80,89, 108,109	8 pol.	E 600.23115	Stiftleiste) Pin bar) wahlweise
	8 pol.	E 435.02532	Kontaktstift) alternat. Contact pin)
	8 pol.	E 600.23127	Federleiste) wahlweise Spring contact strip) alternatively
	2 pol.	E 600.23121	Federleiste) Spring contact strip)
Abb. 1 Pict.1	24 pol.	E 600.23123	Sockel Socket
Abb. 2 Pict.2	40 pol.	E 600.23057	Buchsenleiste Bushing strip
Abb. 3 Pict.3		403.30055	Rohrniet Tubular rivet
Abb. 4 Pict.4		301.00481	Meßpunktstift Measuring point pin