

I/O Karte für Tastatur und Drucker 5
 I/O Board for Keyboard and Printer 5

(SAAG41) AAG41
 702.81764

Position-Nr. Position-No.	Typ Type	Teil-Nr. Part-No.	Bemerkung Remarks
<u>IC - Bausteine / IC - chips</u>			
IC 50, 101	SN 7400 N	E 600.37001	A 01
IC 43, 46	SN 7402 N	E 600.37003	A 02
IC 1, 15, 61 75, 87, 96, 103	SN 7404 N	E 600.37006	A 03
IC 8	SN 7430 N	E 600.37008	A 06
IC 22, 71	SN 7405 N	E 600.37024	A 11
IC 47, 54	SN 7407 N	E 600.37025	A 12
IC 29, 36, 58, 65, 94	SN 7437 N	E 600.37027	A 18
IC 7I, 7II, 14I, 14II, 28I, 28II, 35I, 35II, 42I, 42II, 49I, 49II	SN 75453 BP	E 600.37058	A 28
IC 6, 13, 25, 26, 27, 32, 34, 41, 48, 55, 59, 67, 74, 88, 95, 102, 57	SN 7475 N	E 600.37040	F 04
IC 85, 86, 100	SN 7474 N	E 600.37042	F 06
IC 68, 99, 110	SN 74132 N	E 600.37052	G 04
IC 93II	NE 555	E 600.38013	G 05
IC 106, 107	SN 74221 N	E 600.37048	G 06
IC 2, 9, 16, 23, 30, 37, 44, 51	SN 74151 N	E 600.37015	H 02
IC 64, 92	SN 74155 N	E 600.37050	H 05
IC 12	SN 7493 N	E 600.37021	P 01

Position-Nr. Position-No.	Typ Type		Teil-Nr. Part-No.	Bemerkung Remarks
<u>Transistoren / Transistors</u>				
T 2-5,7, 8,11,14, 16-22, 24-27	BD 675 MPSU 45		E 600.63046 E 600.63041) wahlweise) alternatively
T 6,9,10, 12,13,15, 23	BD 679		E 600.63047	
<u>Dioden / Diodes</u>				
D 2,4-21	1 N 4001		E 600.64042	
D 1	ZPD 8,2		E 600.64108	
<u>Kondensatoren / Capacitors</u>				
C 69,75	220 μ F	40 V	E 600.50010	
C 1,51	100 μ F	16 V	E 600.50061) wahlweise
	100 μ F	16 V	E 600.50070) alternatively
C 4-18,34, 35,21-32, 52,57,60, 61,76,77, 39-46,79	0,1 μ F	100 V	E 600.52032	
C 73	47 μ F	16 V	E 600.50069) wahlweise
	47 μ F	16 V	E 600.50060) alternatively
C 62,63,66, 68,70,71	10 μ F	25 V	E 600.50055	
C 56	0,022 μ F	160 V	E 600.52044	
C 53	0,047 μ F	100 V	E 600.52031	
C 58	1000 pF	100 V	E 600.52025	
C 50,54	680 pF	50 V	E 600.53015	
C 2,3,20, 47-49,55, 59,64,65, 67,72,74, 78	0,1 μ F	16 V	E 600.53010	

Position-Nr. Position-No.	Typ Type		Teil-Nr. Part-No.	Bemerkung Remarks
<u>Widerstände / Resistors</u>				
R 53,54,59, 60,62, 68 - 71, 87,89,61, 120	47 Ohm	1/8 W	E 600.40205	
R 93,119	470 Ohm	1/8 W	E 600.40193	
R 88,90,96, 121	1 kOhm	1/8 W	E 600.40195	
R 81,91	2,2 kOhm	1/8 W	E 600.40212	
R 47,48,50, 51,55 - 58	4,7 kOhm	1/8 W	E 600.40197	
R 1,2, 4 - 25,49, 52,82,92, 94,95,98, 100-108, 36 - 46, 27-30,32	10 kOhm	1/8 W	E 600.40200	
R 83,84	1,5 kOhm	1/3 W	E 600.40033	
R 97	120 kOhm	1/4 W	E 600.40145	
R 66,67,72, 73,109-118	100 Ohm	2 W	E 600.40181	
R 122	6,8 kOhm	1/8 W	E 600.40202	
R 3,85,86	10 kOhm	1/2 W	E 600.44033	
R 63 - 65 74 - 80	100 Ohm	1/4 W	E 600.40108	

Position-Nr. Position-No.	Typ Type	Teil-Nr. Part-No.	Bemerkung Remarks
<u>Allgemeine Teile / General parts</u>			
Sch 1,2	0,1 A 100 V	E 600.85059 E 600.85073	Schalter) wahlweise Switch) alternatively
M 60,72,78, 79,80,89, 109,108	8 pol.	E 600.23115	Stiftleiste) Pin bar) wahlweise
	8 pol.	E 435.02532	Kontaktstift)alternat. Contact pin)
	2 pol.	E 600.23121	Federleiste) Spring contact strip)
	8 pol.	E 600.23127	wahlweise Steckverbindung) alter- Connection natively
Abb. 1 Pict.1	24 pol.	E 600.23123	Sockel Socket
Abb. 2 Pict.2	40 pol.	E 600.23057	Buchsenleiste Bushing strip
Abb. 3 Pict.3		403.30055	Rohrniet Tubular rivet
Abb. 4 Pict.4		301.00481	Meßpunktstift Measuring point pin